

## VINKELVÄXLAR TYP RM

### ANGULAR GEARBOXES TYPE RM

#### Vinkelväxel typ RM med ensidig axel

#### Bevel gearbox type RM with one-sided shaft

Typ Type	Utväxling Ratio	A	B	C	D1 j6	D2 j6	D3 g7	D4 g7	D5	E	F	G	H	L1	L2
RM 12	1, 2, 3	116	72	46	12	12	44	65	54	42	2	74	32.5	26	26
RM 19	1, 2, 3				19									40	
	4, 5	168	105	65	14	19	60	86	72	59	4	100	45.0	30	40
RM 24	1, 2, 3				24									50	
	4, 5	208	130	80	19	24	70	105	88	73	5	115	55.0	40	50
RM 32	1, 2, 3				32									60	
	4, 5	248	155	95	24	32	95	135	115	88	5	145	70.0	50	60
RM 38	1, 2, 3				38									70	
	4, 5	288	180	110	28	38	120	165	145	103	5	170	85.0	60	70
RM 42	1, 2, 3				42									80	
	4, 5	328	205	125	32	42	135	190	165	118	5	195	100.0	60	80
RM 55	1, 2, 3				55									110	
	4, 5	408	260	150	42	55	170	230	205	143	5	245	120.0	80	110

Typ Type	Utväxling Ratio	M	N	O	P	R	S1	S2	C1	C2	T
RM 12	1, 2, 3	100	65	45	M6	M6	M4 x 8	M4 x 8	20 x 4 x 4	20 x 4 x 4	9.5
RM 19	1, 2, 3	140					M6 x 12		32 x 6 x 6	32 x 6 x 6	
	4, 5	130	90	70	M6	M6	M5 x 10	M6 x 12	25 x 5 x 5	35 x 6 x 6	14.0
RM 24	1, 2, 3	165					M8 x 16		40 x 8 x 7		
	4, 5	155	110	88	M8	M8	M6 x 12	M8 x 16	35 x 6 x 6	40 x 8 x 7	18.0
RM 32	1, 2, 3	205					M10 x 20		50 x 10 x 8		
	4, 5	195	140	110	M10	M10	M8 x 16	M10 x 20	40 x 8 x 7	50 x 10 x 8	18.0
RM 38	1, 2, 3	240					M12 x 24		63 x 10 x 8	63 x 10 x 8	
	4, 5	230	170	136	M12	M12	M10 x 20	M12 x 24	50 x 8 x 7	60 x 10 x 8	18.0
RM 42	1, 2, 3	275					M12 x 24		70 x 12 x 8		
	4, 5	255	200	155	M12	M12	M10 x 20	M12 x 24	50 x 10 x 8	70 x 12 x 8	18.0
RM 55	1, 2, 3	355					M14 x 28		100 x 16 x 10		
	4, 5	325	240	190	M14	M14	M12 x 24	M14 x 28	70 x 12 x 8	100 x 16 x 10	23.0

Fet stil = lagervara på fabrik

*Bold = in stock*